



Nortec 2000D+ Flaw Detector

FEATURES

- 50 Hz - 12 MHz frequency range
- Single Li-Ion battery
- Lightweight, less than 4lbs. (1.8 Kg)
- Digital conductivity in International Annealed Copper Standard (%IACS) or Mega Siemens per meter (MS/m)
- Non-conductive coating readings in inches or millimeters
- Multiple scanner support
- Internal balance loads for single coil probe support
- Customer interchangeable displays:
 - Hi-Brite Electroluminescent
 - Monochrome Liquid Crystal
 - Color Liquid Crystal
- Dual Frequency
- VGA Output
- Display Freeze to hold flaw signals
- PowerLink™ Technology - automatic probe recognition and instrument set-up
- Split screen presentation with color coded soft keys
- On screen reference memory for go/no go applications
- On board storage of 120 programs
- Waterfall display
- Windows-based EddyMaster™ Software

DUAL FREQUENCY EDDY CURRENT FLAW DETECTOR

The Nortec 2000D+ offers a frequency range of 50 Hz to 12 MHz for applications ranging from detection of cracks in tubes or structures to the discovery of minute flaws in aircraft materials. Single or dual frequency operation, easy to use digital conductivity, and rotating scanner support make the flaw detector ideal for numerous aerospace NDT applications.

Customer-interchangeable displays offer excellent visibility in any lighting condition. A VGA output drives a heads up display for inspection where conditions may be cramped or a large desktop monitor or projector for classroom training.

At less than 4 lbs (1.8 Kg), the rugged Foreign Object Debris (FOD) free case will survive harsh field and production environments. An adjustable tilt bail and

anti-slip bumper allow the unit to be placed on just about any surface.

The Nortec 2000D+ incorporates our unique PowerLink™ software, which provides automatic probe recognition and documentation. The instrument can be set-up by recalling the program stored in the PowerLink™ chip, providing integrity and repeatability of inspection results.

As many as 120 programs can be stored and recalled later. Date and time are recorded with each set-up and are easily identified with alphanumeric values up to 29 characters long. 20 memory locations are available to store eddy current displays.

NORTEC 2000D+ SPECIFICATIONS*

BASIC PERFORMANCE

Frequency Range: 50 Hz - 12 MHz

Gain: 0 - 90 dB in 0.1 dB steps. The horizontal and vertical gains may be adjusted separately or together.

Rotation: Variable 0° - 359°

Sweep: Variable from 0.005 - 4 seconds per division

Low Pass Filter: 10 - 500 Hz and wide band

High Pass Filter: Off, 2 to 500 Hz. 2 pole response

Probe Drive: 2, 6, 12 volts

Variable Persistence: Screen persistence can be varied from 0.1 - 5 seconds.

Probe Types: Absolute and differential in either bridge or reflection configuration. The instrument is fully compatible with NORTEC PowerLink™ probes.

Alarms: Can be set to trigger on positive or negative

Alarm Modes: 1-3 box gates, polar, sweep, conductivity, and coating thickness

Trace Storage: 20 traces can be stored for recall. The traces can be static or frozen. They can contain up to 60 seconds of movement. The traces are stored with the date and time of capture.

Program Storage: 120 instrument set-ups may be stored and recalled. The date and time of storage is recorded with each set-up.

Print Out: Provides a custom configurable report header containing the display screen data and probe parameters including serial number (PowerLink™ probes only)

Printers: Any serial printer

INPUTS / OUTPUTS

Power: 7-pin connector to charge the internal battery and operate the instrument on AC power

RS-232: DB-9P connector, bi-directional serial data via RS-232

Probe Connector: 16-pin LEMO

Analog Outputs: Horizontal and Vertical outputs of both F1 and F2. +/- 5 volts, 1 volt per division

Alarm Outputs: 9-pin analog and alarm output connector

VGA Output

GENERAL

Dimensions:
9.5" L x 5.5" H x 3.6" D
215 mm x 165 mm x 92 mm

Weight: 3.8 lbs. (1.7 Kg) with battery

Display: Customer-interchangeable QVGA displays (320 x 240 pixels): color or monochrome LCD, Hi-Brite electroluminescent

Operating Temperature:
14° to 131° F (-10° to 55° C),
depending on configuration

Storage Temperature:
-60° to 160° F (-51° to 71° C),
depending on configuration

Humidity: 5 to 95%

Classification: Based on Class 2 specifications from the MIL-PRF-28800F handbook

Altitude: Maximum operating and non-operating altitude - 15,000 ft. (4600 m)

Hazardous Area Operation: Safe operation as defined by Class I, Division 2, Group D, as found in the National Fire Association Code (NFPA 70), Section 500, and tested using MIL-STD-810F, Method 511.4, Procedure 1

POWER

Power Requirements: 85 to 240 volts, 50-60 Hz. External holder charges batteries outside the instrument. Charging time is typically 4 hours.

Low Battery Protection: Display bar graph "gas gauge" indicates approximate operating time.

Battery Operating Time: 8 hours (nominal depending on configuration)

CONDUCTIVITY

Frequency: 60 kHz or 480 kHz

Probe Type: NORTEC Conductivity Probe

Digital Conductivity Specification: Digital conductivity display from 0.9% to 110% IACS or 0.5 to 64 MS/m. Accuracy within +/- 0.5% IACS from 0.9% to 65% IACS and within +/- 1.0% of values over 62%. Meets or exceeds BAC 5651 specifications.

Non-Conductive Coating Thickness: Can measure non-conductive coating thickness from 0" to 0.015" (0 to 0.38 mm). Accuracy of +/- 0.001" (0.025 mm) over 0.00 to 0.015" (0 to 0.38 mm) range

SCANNERS

Scanner Compatibility: Will operate all NORTEC and other commercially available scanners

Waterfall Display: Stores up to 60 sweeps per hole and includes an on screen readout of the distance to the defect from the start of the scan (PS-5 only)

DUAL FREQUENCY

Frequency Extension: 50 Hz to 12 MHz

Second Frequency: 50 Hz to 3 MHz, 2nd frequency is an exact division of the first frequency in ratios of: 1/2 (F1 < 6 MHz), 1/4, and even divisors to 1/32.

Display: Frequency 1 (F1) only, Frequency 2 (F2) only, sum of F1 and F2, difference between F1 and F2, split screen with selected combinations of F1 and F2 and mixed frequencies

High Pass Filter: Available in Frequency 1 (F1) only



OLYMPUS

Printed 12/2005
© 2005 Olympus NDT, All Rights Reserved.
*All specifications are subject to change without notice.
Olympus and the Olympus logo are registered trademarks of Olympus Corporation.
Innovation in NDT is a trademark of Olympus NDT Corporation.
NORTEC and SONIC are trademarks of Olympus NDT.
Other company or product names mentioned in this document may be trademarks or registered trademarks of their respective companies



**EI. Venizelou 7 & Delfon, Metamorfoisi
14452 Athens, Greece**

**tel: +30 210 2846 801-4, fax: +30 210 2846 805
sales@envirocoustics.gr, www.envirocoustics.gr**